



## Palm™ handheld/GSM compatibility matrix

Manufacturer	Model	Data Inside	Infrared (IrDA)	Cable*	TDK Global Pulse™*	Palm V™ modem*	Bluetooth
<b>Ericsson</b>	GH/GF/PF 600 series	-	● <sup>1,6</sup>	-	●	● <sup>5</sup>	-
	GF/PF 700 series	-	● <sup>1,6</sup>	-	●	● <sup>5</sup>	-
	A 1018	-	● <sup>1,6</sup>	-	●	● <sup>5</sup>	-
	<b>A 2618</b>	-	● <sup>2,6</sup>	-	●	-	-
	S 868	-	● <sup>1,6</sup>	-	●	● <sup>5</sup>	-
	SH 888/I 888	●	● <sup>6</sup>	-	●	● <sup>5</sup>	-
	T 10	-	● <sup>1,6</sup>	-	●	● <sup>5</sup>	-
	T 18	-	● <sup>1,6</sup>	-	●	● <sup>5</sup>	-
	T 28 (all versions)	-	● <sup>2,6</sup>	-	-	-	-
	<b>R 310</b>	-	● <sup>2,6</sup>	-	●	-	-
	R 320	●	● <sup>6</sup>	-	-	-	-
	R 380	●	● <sup>6</sup>	-	-	-	-
	<b>T 36m</b>	●	● <sup>6</sup>	-	-	-	● <sup>9*</sup>
<b>Motorola</b>	Timeport L7089**	●	● <sup>6</sup>	-	● <sup>8</sup>	-	-
	Timeport P7389/7389e**	●	● <sup>6</sup>	-	● <sup>8</sup>	-	-
	<b>Timeport P1088</b>	●	● <sup>6</sup>	-	-	-	-
	Timeport 250	●	● <sup>6</sup>	-	● <sup>8</sup>	-	-
	V 3688 / V 3690	-	-	-	● <sup>8</sup>	-	-
	V 50	-	-	-	● <sup>8</sup>	-	-
<b>Nokia</b>	5100 series	-	-	-	●	● <sup>5</sup>	-
	6100 series	-	-	-	●	● <sup>5</sup>	-
	6210	●	● <sup>6</sup>	-	-	-	-
	6250	●	● <sup>6</sup>	-	-	-	-
	7110	●	● <sup>6</sup>	-	-	-	-
	8210	●	● <sup>6</sup>	-	-	-	-
	8810	●	● <sup>6</sup>	-	-	-	-
	8850	●	● <sup>6</sup>	-	-	-	-
<b>Sagem</b>	MC 755 X	● <sup>7</sup>	-	● <sup>3</sup>	-	-	-
	MC/RC 84x / 85x / 8300	● <sup>7</sup>	-	● <sup>3</sup>	-	-	-
	MC/MW 94x / 95x / 9500	● <sup>7</sup>	-	● <sup>4</sup>	-	-	-
<b>Samsung</b>	A 100/ A 110	●	● <sup>6</sup>	-	-	-	-
<b>Siemens</b>	S 25	●	● <sup>6</sup>	-	-	-	-
	S 35i	●	● <sup>6</sup>	-	-	-	-
	<b>S 40</b>	●	● <sup>6</sup>	-	-	-	-
	<b>SL 45</b>	●	● <sup>6</sup>	-	-	-	-
<b>Trium</b>	<b>Cosmo</b>	●	● <sup>6</sup>	-	-	-	-

**NOTE:** "Data Inside" designates a phone with an internal hardware modem.

<sup>1</sup> Requires Ericsson DI-27 infrared adapter\*.

<sup>2</sup> Requires Ericsson DI-27 infrared adapter\*.

<sup>3</sup> Requires Sagem 7xx/8xx series data cable\*.

<sup>4</sup> Requires Sagem 9xx series data cable\*.

<sup>5</sup> Requires Palm™ GSM upgrade kit\*.

<sup>6</sup> Requires PalmOS™ infrared update (not necessary with Palm™ Vx, IIIc, IIIe, IIIxe, m100 or later).

<sup>7</sup> Class 1 only fax modem.

<sup>8</sup> Requires Motorola SmartCELlect™ 2000 (PCC7000) and Palm™ V (PCC7005) or Palm™ III (PCC7003) cable\*.

<sup>9</sup> Requires Palm™ compatible Bluetooth adapter\*.

\* Products sold separately.

\*\***IMPORTANT:** Launch infrared connection from Palm™ handheld **BEFORE** activating IR port on phone.

**BOLD TYPE = PHONE NOT TESTED**

**STANDARD SETTINGS\*\*\* (Infrared):** Speed 57,600 bps, Flux ctl: automatic, Init string.: AT&FX4

\*\*\***CAUTION:** These settings may vary depending on type of network, operator or applications used.